Quality and reliability is our tradition.

NE





Earth Resistance Tester Series are small, lightweight and dust & drip-proof.



Find Quality Products Online at:

www.GlobalTestSupply.com

sales@GlobalTestSupply.com

KYOR ITSU ELECTRICAL INSTRUMENTS WORKS , LTD .

INSTRUMENT LAYOUT




q q

Q

Digital Earth Tester MODEL 4105A Scale Board OK Lamp Press To Test Button Range Selector Switch LCD Display Indication LED With Test Leads Auxiliary Earth Spikes Simplified Measurement Probe Safery Alligator Clip Test Bar

ACCESSORIES



MODEL7095 MODE

MODEL8032 MODEL7127

SPECIFICATIONS	

	Model 4102A/4102A-H	Model 4105A/4105A-H	
Measurement Ranges	Earth Resistance:0-12 /0-120 /0-1200 Earth Voltage(50,60Hz)0-30V AC	Earth Resistance:0-20 /0-200 /0-2000 Earth Voltage(50,60Hz)0-200V AC	
Accuracy	Earth Resistance: ± 3% of full scale Earth Voltage: ± 3% of full scale	Earth Resistance: ± 2%rdg ± 0.1 (20 range) ± 2%rdg ± 3dgt(200 /2000 range) Earth Voltage: ± 1%rdg ± 4dgt	
Overload Protection	Earth Resistance:276V AC for 10 seconds across 2 of the 3 terminals Earth Voltage:276V AC for 1 minute	Earth Resistance:280V AC for 10 seconds across 2 of the 3 terminals Earth Voltage:300V AC for 1 minute	
Safety Standard	IEC61010-1 CAT. 300V Pollution Degree 2,IEC61557		
Applicable Standards	IEC60529 IP54		
Withstand Voltage	3700V AC for 1 minute		
Power Source	R6P(AA (1.5V) x6		
Dimensions	105(L) x158(W) x70(D)mm		
Weight	600g approx. 550g approx.		
Accessories7095(Test Leads)× 1set(red-20m,yellow-10m, 8032(Auxiliary earth spikes)× 1set 7127(Simplified measurement probe)× 1set R6P(AA)× 6, Neck strap, Instruction Manual	7095(Test Leads)× 1set(red-20m,yellow-10m,green-5	5m) Carrying Case	
	7127(Simplified measurement probe)× 1set	Soft Case(4012A,4105A) Hard Case(4012A-H,4105A-H)	



Please read the "Safety Warnings" in the instruction manual supplied with the instrument thoroughly and completely for correct use. Failure to follow the safety rules can cause fire, trouble, electrical shock, etc. Therefore, make sure to operate the instrument on a correct power supply and voltage rating

marked on each instrument.

www.GlobalTestSupply.com

The contents of this catalogue may be subject to change without notice.

D ISTR BUTOR



KYOR ITSU ELECTRICAL INSTRUMENTS WORKS ,LTD .

No. 5-20 Nakane 2-chome, Meguro-ku, Tokyo, 152-0031 Japan Phone & 1-3-3723-0131 Fax & 1-3-3723-0152 URL http://www.kew-ltd.co.jp Fmail:hb/@_kew-ltd.co.jp

Find Quality Products Online at:

sales@GlobalTestSupply.com