

TECHNICAL DATA



Features

- Tests phase orientation of 3-phase power sources
- Indicates phase orientation (clockwise or counter-clockwise) and whether each of the three phases is live
- LEDs display motor rotation and phase status
- Easy to open alligator clips with wide jaws
- Durable double molded plastic housing
- Cat. III 600V safety rating
- Includes three color coded cables, three alligator clips, battery and soft carrying case

R5004-KIT

Phase Rotation/Clamp Meter Kit

Includes:

- R5004 Motor Rotation and 3-Phase Tester;
- R5040 AC/DC Clamp Meter;
- R2990 Thermocouple Adapter;
- R5110 Non-Contact Voltage Detector;
- TP-01 Beaded Thermocouple Wire Probe;
- R1000 Safety Test Lead Set, Double Insulated
- and R9950 Carrying Case



Specifications

Nominal Voltage	1 to 400V AC
Rotary Direction:	120 to 400V AC
Nominal Voltage Phase Indirection:	2 to 400Hz
Frequency:	

General Specifications

Power Supply:	9V Battery
Battery Life: Overvoltage	Approx. 1 year (regular usage)
Category: Product	CAT. III 600V, CAT. IV 300V CE
Certifications:	0 to 122°F (0 to 50°C)
Operating Temperature:	-4 to 140°F (-20 to 60°C)
Storage Temperature:	
Operating Humidity Range:	10 to 80%
Dimensions:	5.1 x 2.7 x 1.3" (130 x 68 x 32 mm)
Weight:	4.5oz (130g)

Model	Description
R5004	Motor Rotation and 3-Phase Tester
CA-05A	Soft Carrying Case
R1210	Alligator Clip Set, Large
R5004-KIT	Phase Rotation/Clamp Meter Kit
R5004-NIST	Motor Rotation and 3-Phase Tester & NIST